

**REVISIONS**

REV	DATE	MF
DR	CK	APP
W.O. #		
DESCRIPTION		
0	5/10/2006	
AE		
W.O. # 38124-37		

(Note 2)

3 PHASE- CROSS ARM  
4kV OR 26kV  
(Note 1A)

10' CLR.

TRANSFORMER  
(Note 1A)

10' CLR.

SECONDARY  
(Note 1B)

5' CLR.

Street Light  
Fiber Optic  
Cable TV  
Telephone

PLANTING  
STRIP

STREET SIDE

SIDE WALK

## REFERENCES

FOR REFERENCES, SEE TA-2000

## NOTES

1. VEGETATION CLEARANCE CRITERIA IS BASED ON WAC-296-24-960, RCW 64.12.035 AND SEATTLE CITY LIGHT BEST PRACTICE

### CONDUCTOR TYPE

### CLEARANCE

- A. PRIMARY DISTRIBUTION, 4KV-26KV AND TRANSFORMER, SWITCHES & ELECTRICAL EQUIPMENT ON THE POLE ... 10'
- B. SECONDARY, FIBER OPTIC, CABLE TV AND TELEPHONE CABLE ..... 5'
- C. TRANSMISSION CONDUCTOR, VOLTAGE > 26KV (NOT SHOWN) APPLICABLE IN SOME LOCATIONS ..... 16.5'

2. ILLUSTRATION IS SHOWN FOR A TYPICAL 47' POLE, AND CLEARANCE AT THE POLE. ABOVE CRITERIA ALSO APPLY TO OTHER POLE HEIGHTS AND TO CONDUCTOR/WIRE TO TREE CLEARANCE ALONG THE SPAN

## OVERHEAD DISTRIBUTION NORTH & SOUTH DISTRIBUTION

3 PHASE DISTRIBUTION POWERLINE  
TREE CLEARANCE  
SIDE PRUNING - DECIDUOUS



Seattle City Light

DR: A. EDENS

DATE: 05/10/2006

CLASS

CK:

14

APP: DBS

L

5/10/06

5-12-06

DRAWING NO.

SCALE NONE

REV. NO. 0

TA-2003